




Anode 1 : E
+HT : A
HP+ : G
HP - : I



EI 84b (Noyau 28 x 45mm) 0,6W/Kg (M6X)
Cale entrefer: 0,75mm



DA143 Transformateur de sortie SE.

3000 Ohms/ 8 Ohms. Ia0: 70mA, Rpri: 200 Ohms

30Hz/70Khz -1dB @8Watts.

LP/LL//Cshunt : 20H/3mH //650pF. Pertes < 0,5dB (10%)

Copyleft Yves Monmagnon. Oct. 2009